


# Mapping to the POLS Black & White Printer

## Download the Printer Driver

1. In a web browser, navigate to: <https://support.hp.com/us-en/drivers/selfservice/hp-laserjet-enterprise-mfp-m630-series/6771914>
2. Expand “Driver-Product Installation Software”
3. Expand “Basic Drivers”
4. Scroll down to “HP LaserJet Flow M630z, M630h, M630zm, and M630hm Printer Series PCL 6 Driver (no Installer)”, then click Download.
5. Once downloaded, double click the EXE file.
6. Click “Install anyway” in the Microsoft pop-up.


[Get apps from Store](#) [Install anyway](#)

7. Click “Yes” to extract the files to your C:\ drive.




## Install the Printer

1. On the bottom left of your desktop, click on the Windows Start Menu icon.
2. Click on the gear icon to open up Windows Settings.
3. Click on the “Devices” tab.



**4. Click on the “Printers & Scanners” tab.**



- 5. Click on “Add a printer or scanner.”**
- 6. Wait until the option “The printer that I want isn’t listed” appears at the end of the list of found printers, then click it.**

# Printers & scanners

## Add printers & scanners



Refresh

Searching for printers and scanners

•••••

[The printer that I want isn't listed](#)

7. Click on “Add a printer using a TCP/IP address or hostname” checkbox, then click Next.

The screenshot shows the Windows 'Add Printer' wizard. Step 1: Find a printer by other options. It includes a back arrow, a printer icon, and the text 'Add Printer'. Below are two radio button options: 'My printer is a little older. Help me find it.' and 'Select a shared printer by name'. A 'Browse...' button is next to a text input field containing placeholder text: 'Example: \\computername\printername or http://computername/printers/printername/.printer'. At the bottom, there are three radio button options under 'Add a printer using a TCP/IP address or hostname': 'Add a printer using a TCP/IP address or hostname' (selected), 'Add a Bluetooth, wireless or network discoverable printer', and 'Add a local printer or network printer with manual settings'.

8. Ensure that “Device type” is set to “Autodetect.”
9. For the “Hostname or IP address” field, enter in the following DNS name:  
The Port name will automatically copy from the Hostname.

HP LaserJet Enterprise MFP M630 : p\_15\_303\_1.printer.isu.edu



Type a printer hostname or IP address

Device type:

Autodetect

Hostname or IP address:

p\_07\_224\_1.engr.isu.edu

Port name:

p\_07\_224\_1.engr.isu.edu

Query the printer and automatically select the driver to use

Next

Cancel

10. You may be asked to select a driver. If you are presented with a list of drivers, like the one shown below, click Have Disk..., then click Browse.



### Install the printer driver



Choose your printer from the list. To install the driver from an installation CD, click Have Disk.

Manufacturer

Adobe

Canon

Generic

**HP**

Microsoft

Printers

HP Color LaserJet 1600 Class Driver

HP Color LaserJet 2600n Class Driver

HP Color LaserJet CP1213 Class Driver

HP Color LaserJet CP1214 Class Driver

HP Color LaserJet CP1215 Class Driver

This driver is digitally signed.


[Tell me why driver signing is important](#)

Have Disk...


Next

Cancel

11. Navigate to your C:\ drive and click on the driver packet downloaded earlier, then click Open.




12. The correct .inf file should automatically populate next to "File name". Click Open once more.



13. Back in the "Install From Disk" window, click OK.

14. With the driver now selected in the "Install the printer driver" window, click Next.

15. After the printer has been contacted, the following window will pop up. Feel free to name the printer.



16. Printer sharing is entirely optional. Feel free to use your own judgement here. Click Next when you have completed this step.

X



←  Add Printer

## Printer Sharing

If you want to share this printer, you must provide a share name. You can use the suggested name or type a new one. The share name will be visible to other network users.

- Do not share this printer  
 Share this printer so that others on your network can find and use it

Share name:	<input type="text" value="NPIBD94FE (HP Color LaserJet MFP M477fdn)"/>
Location:	<input type="text"/>
Comment:	<input type="text"/>

 Next  Cancel

17. Done! Feel free to print off a test page to confirm the process has completed successfully.